# **PSD** series power supply

Desktop type power supply 12V DC



**PSD12050** CODE: v2.0/X

PSD 12V/5A Desktop type power supply for CCTV NAME:

## Features of power supply:

- power output 5A/12 V DC\*
- universal AC input voltage range ~100 - 240 V
- · high efficiency 89%
- · LED optical signalisation
- standby power <0,21W
- · efficiency level: VI
- protections:
  - · SCP short-circuit protection
  - · overvoltage protection (AC input)
  - · overload (OLP)
- · warranty 2 years from production date




## **DESCRIPTION**

Stabilized DC power supply is intended for supply CCTV cameras that require stabilised voltage of 12 V DC. The unit has a cable with a DC5.5/2.1 plug. When connected to fuse blocks of the LB4/xx/xx or LB8/xx/xx family, the power supply unit can feed more cameras (max. 4 or 8). The unit is protected against short-circuit and overload.

#### **SPECIFICATIONS**

Supply voltage	~100 - 240 V; 50/60 Hz
Current consumption	1,2 A
Supply power	60 W max.
Efficiency (average)	89%
Efficiency (10% load)	88%
Output voltage	12 V DC
Output current t <sub>AMB</sub> <30°C	5A - refer to graph 1.
Output current t <sub>AMB</sub> =40°C	3,5A - refer to graph 1.
Ripple voltage	100 mV p-p max.
Short-circuit protection SCP	electronic, automatic recovery
Overload protection OLP	105-150% of power supply, automatic recovery
Optical signalisation	LED – presence of DC voltage
Operating conditions	Temperature: 0°C ÷ +40°C, relative humidity 20%90%, without condensation
Dimensions (LxWxH)	116 x 54 (80) x 35 [mm]
Net/gross weight	0,30 / 0,34 [kg]
Protection class EN 62368-1	II (second)
Length of DC cable	1,45m + plug DC5,5/2,1 female
Length of AC cable	1,15m + mains plug
Storage temperatu	-20°C+60°C

<sup>\*</sup> In order to extend the life of the power supply, the load current of 3,5A is recommended.



Relation between output current and ambient temperature (instantaneous load).





Fig.1 Dimension of power supply.

#### **ACCESORIES**



For power supplies are available accessories - fuse blocks and cable adapter. For details -visit www.pulsar.pl.

<sup>\*</sup> Refer to graph 1









