



























## Features

- Constant Voltage + Constant Current mode output
- Metal housing with class I design
- · Built-in active PFC function
- · Class 2 power unit
- IP67 / IP65 rating for indoor or outdoor installations
- Function options: output adjustable via potentiometer; 3 in 1 dimming; Timer dimming
- Typical lifetime > 62000 hours
- 7 years warranty


## Applications

- · LED street lighting
- LED high-bay lighting
- Parking space lighting
- · LED fishing lamp
- LED greenhouse lighting
- Type "HL" for use in Class I, Division 2 hazardous (Classified) location.

## Description

HLG-100H series is a 100W AC/DC LED driver featuring the dual mode constant voltage and constant current output. HLG-100H operates from 90 ~ 305VAC and offers models with different rated voltage ranging between 20V and 54V. Thanks to the high efficiency up to 93%, with the fanless design, the entire series is able to operate for  $-40^{\circ}\text{C} \sim +80^{\circ}\text{C}$  case temperature under free air convection. The design of metal housing and IP67/IP65 ingress protection level allows this series to fit both indoor and outdoor applications. HLG-100H is equipped with various function options, such as dimming methodologies, so as to provide the optimal design flexibility for LED lighting system.

## Model Encoding



Type	IP Level	Function	Note
Blank	IP67	Io and Vo fixed	In Stock
Α	IP65	Io and Vo adjustable through built-in potentiometer	In Stock
В	IP67	3 in 1 dimming function (1~10VDC, 10V PWM signal and resistance)	In Stock
AB	IP65	Io and Vo adjustable through built-in potentiometer & 3 in 1 dimming function (1~10Vdc, 10V PWM signal and resistance)	In Stock
D	IP67	Timer dimming function, contact MEAN WELL for details(safety pending).	By request




#### **SPECIFICATION**

MODEL		HLG-100H-20	HLG-100H-24	HLG-100H-30	HLG-100H-36	HLG-100H-42	HLG-100H-48	HLG-100H-54
ОИТРИТ	DC VOLTAGE	20V	24V	30V	36V	42V	48V	54V
	CONSTANT CURRENT REGION Note.4	10 ~ 20V	12 ~ 24V	15 ~ 30V	18 ~ 36V	21 ~ 42V	24 ~ 48V	27 ~ 54V
	RATED CURRENT	4.8A	4A	3.2A	2.65A	2.28A	2A	1.77A
	RATED POWER	96W	96W	96W	95.4W	95.76W	96W	95.58W
	RIPPLE & NOISE (max.) Note.2	150mVp-p	150mVp-p	200mVp-p	200mVp-p	200mVp-p	200mVp-p	200mVp-p
	VOLTAGE AD L BANGE	Adjustable for A/A	AB-Type only (via l	built-in potentiome	ter)			
	VOLTAGE ADJ. RANGE	17 ~ 22V	22 ~ 27V	27 ~ 33V	33 ~ 40V	38 ~ 46V	43 ~ 53V	49 ~ 58V
	CURRENT AR L DAVIGE	Adjustable for A/AB-Type only (via built-in potentiometer)						
	CURRENT ADJ. RANGE	3 ~ 4.8A	2.5 ~ 4A	2~3.2A	1.65 ~ 2.65A	1.4 ~ 2.28A	1.25 ~ 2A	1.1 ~ 1.77A
	VOLTAGE TOLERANCE Note.3	±1.0%	±1.0%	±1.0%	±1.0%	±1.0%	±1.0%	±1.0%
	LINE REGULATION	±0.5%	±0.5%	±0.5%	±0.5%	±0.5%	±0.5%	±0.5%
	LOAD REGULATION	±0.5%	±0.5%	±0.5%	±0.5%	±0.5%	±0.5%	±0.5%
	SETUP, RISE TIME Note.6	1200ms.50ms/11	5VAC 500ms,50	ms/230VAC				
	HOLD UP TIME (Typ.)	16ms / 115VAC, 2						
	(')	90 ~ 305VAC 127 ~ 431VDC						
	VOLTAGE RANGE Note.5							
	FREQUENCY RANGE	47 ~ 63Hz						
	TREGOLINGTRANGE		DE>0.05/220\/A	C DE>0 02/277\/	AC @ full load			
	POWER FACTOR (Typ.)	PF≥0.98/115VAC, PF≥0.95/230VAC, PF≥0.93/277VAC @ full load						
		(Please refer to "POWER FACTOR (PF) CHARACTERISTIC" section)						
	TOTAL HARMONIC DISTORTION	THD< 20% (@ load≥60% / 115VAC,230VAC; @ load≥75% / 277VAC)   (Please refer to "TOTAL HARMONIC DISTORTION (THD)" section)						
NPUT	EEFICIENOV (T. )	`			· · · · · · · · · · · · · · · · · · ·	000/	000/	000/
	EFFICIENCY (Typ.)	93%	93%	93%	93%	93%	93%	93%
	AC CURRENT (Typ.)	1.2A / 115VAC	0.55A / 230VAC					
	INRUSH CURRENT (Typ.)	COLD START 60A(twidth=415µs measured at 50% lpeak) at 230VAC; Per NEMA 410						
	MAX. No. of PSUs on 16A CIRCUIT BREAKER	4 units (circuit breaker of type B) / 8 units (circuit breaker of type C) at 230VAC						
	LEAKAGE CURRENT	<0.75mA / 277VA	C					
	OVER OURRENT	95 ~ 106%						
	OVER CURRENT	Constant current limiting, recovers automatically after fault condition is removed						
	SHORT CIRCUIT	Constant current	limiting, recovers a	utomatically after fa	ault condition is ren	noved		
PROTECTION		23 ~ 27V	28 ~ 34V	34 ~ 38V	41 ~ 46V	47 ~ 53V	54 ~ 63V	59 ~ 65V
	OVER VOLTAGE	Shut down o/p vo	Itage with auto-reco	overy or re-power o	n to recovery		1	I
	OVER TEMPERATURE	Shut down o/p voltage, recovers automatically after temperature goes down						
	WORKING TEMP.	·	°C (Please refer to	•	<u> </u>			
	MAX. CASE TEMP.	Tcase= +80°C	(					
	WORKING HUMIDITY	20 ~ 95% RH non	-condensing					
ENVIRONMENT		-40 ~ +80°C, 10 ~						
	STORAGE TEMP., HUMIDITY	±0.03%/°C (0~						
	TEMP. COEFFICIENT	,		16 70 : 1				
	VIBRATION	10 ~ 500Hz, 5G 12min./1cycle, period for 72min. each along X, Y, Z axes						
SAFETY & EMC	SAFETY STANDARDS Note.8	UL8750(type"HL"), CSA C22.2 No. 250.0-08; EN/AS/NZS 61347-1, EN/AS/NZS 61347-2-13 independe IP65 or IP67, J61347-1, J61347-2-13(except for B,AB and D-type), KC61347-1, KC61347-2-13(except f EAC TP TC 004 approved; design refer to UL60950-1, TUV EN60950-1						
	WITHSTAND VOLTAGE	I/P-O/P:3.75KVAC I/P-FG:2KVAC O/P-FG:1.5KVAC						
	ISOLATION RESISTANCE							
		I/P-O/P, I/P-FG, O/P-FG:100M Ohms / 500VDC / 25°C / 70% RH   Compliance to EN55015, EN55032 Class B, EN61000-3-2 Class C (@ load ≥60%); EN61000-3-3,GB17743 and GB17625.1, EAC TP TC 020						
	EMC IMMUNITY	Compliance to EN30013, EN30032 Class B, EN61000-3-2 Class C (@ load = 00%), EN61000-3-3,0617743 and GB17025.1, EAC 12 12 C C Compliance to EN61000-4-2,3,4,5,6,8,11, EN61547, EN55024, light industry level (surge immunity Line-Earth 4KV, Line-Line 2K EAC TP TC 020						
OTHERS	MTBF	192.2K hrs min.	MIL-HDBK-217F	(25°C)				
	DIMENSION	220*68*38.8mm (		(-v - )				
	PACKING	1.12Kg; 12pcs/14	,					
		0. 1		C input rated cur	ent and 25°C of o	mhient temperatur	΄Α	
NOTE	Ripple & noise are measure     Tolerance : includes set up	eters NOT specially mentioned are measured at 230VAC input, rated current and 25°C of ambient temperature.  noise are measured at 20MHz of bandwidth by using a 12" twisted pair-wire terminated with a 0.1uf & 47uf parallel capacitor.  : includes set up tolerance, line regulation and load regulation.						

- 4. Please refer to "DRIVING METHODS OF LED MODULE".
- 5. De-rating may be needed under low input voltages. Please refer to "STATIC CHARACTERISTIC" sections for details.
- 6. Length of set up time is measured at first cold start. Turning ON/OFF the driver may lead to increase of the set up time.
- 7. The driver is considered as a component that will be operated in combination with final equipment. Since EMC performance will be affected by the complete installation, the final equipment manufacturers must re-qualify EMC Directive on the complete installation again.
- 8.To fulfill requirements of the latest ErP regulation for lighting fixtures, this LED driver can only be used behind a switch without permanently
- 9. This series meets the typical life expectancy of >62,000 hours of operation when Tcase, particularly (c) point (or TMP, per DLC), is about 80°C or less.
- 10. Please refer to the warranty statement on MEAN WELL's website at http://www.meanwell.com
- 11. The ambient temperature derating of 3.5°C/1000m with fanless models and of 5°C/1000m with fan models for operating altitude higher than 2000m(6500ft).
- 12. For any application note and IP water proof function installation caution, please refer our user manual before using. https://www.meanwell.com/Upload/PDF/LED\_EN.pdf


#### ■ BLOCK DIAGRAM

Fosc: 100KHz



#### ■ DRIVING METHODS OF LED MODULE

※ This series is able to work in either Constant Current mode (a direct drive way) or Constant Voltage mode (usually through additional DC/DC driver) to drive the LEDs.




Typical output current normalized by rated current (%)

In the constant current region, the highest voltage at the output of the driver depends on the configuration of the end systems.


Should there be any compatibility issues, please contact MEAN WELL.

## ■ DIMMING OPERATION




#### imes 3 in 1 dimming function (for B/AB-Type)

- $\cdot \ \mathsf{Output} \ \mathsf{constant} \ \mathsf{current} \ \mathsf{level} \ \mathsf{can} \ \mathsf{be} \ \mathsf{adjusted} \ \mathsf{by} \ \mathsf{applying} \ \mathsf{one} \ \mathsf{of} \ \mathsf{the} \ \mathsf{three} \ \mathsf{methodologies} \ \mathsf{between} \ \mathsf{DIM+} \ \mathsf{and} \ \mathsf{DIM-} \mathsf{ind} \ \mathsf{one} \ \mathsf{one$ 
  - 1 ~ 10VDC, or 10V PWM signal or resistance.
- Direct connecting to LEDs is suggested. It is not suitable to be used with additional drivers.
- Dimming source current from power supply:  $100\mu A$  (typ.)
- O Applying additive 1 ~ 10VDC




"DO NOT connect "DIM- to -V"

O Applying additive 10V PWM signal (frequency range 100Hz ~ 3KHz):





"DO NOT connect "DIM- to -V"


Applying additive resistance:



"DO NOT connect "DIM- to -V"











Note: In the case of turning the lighting fixture down to 0% brightness, please refer to the configuration as follow, or please contact MEAN WELL for other options.




Using a switch and relay can turn ON/OFF the lighting fixture.









# ■ LIFE TIME












#### ■ WATERPROOF CONNECTION


#### Waterproof connector

 $Water proof connector \ can be \ assembled \ on \ the \ output \ cable \ of \ HLG-100H \ to \ operate \ in \ dry/wet/damp \ or \ outdoor \ environment.$ 




Size	Pin Configuration (Female)			
M12	000	000		
IVITZ	4-PIN	5-PIN		
	5A/PIN	5A/PIN		
Order No.	M12-04	M12-05		
Suitable Current	10A max.	10A max.		

Size	Pin Configuration (Female)		
M15	(o)		
IVIII	2-PIN		
	12A/PIN		
Order No.	M15-02		
Suitable Current	12A max.		




#### ※ Cable Joiner



 $\bigcirc$  CJ04 cable joiner can be purchased independently for user's own assembly. MEAN WELL order No. : CJ04-1, CJ04-2.

O Junction box option is available for A / Blank - Type. Please contact MEAW WELL for details.

## % Junction Box Option



# ■ INSTALLATION MANUAL

Please refer to:http://www.meanwell.com/manual.html